

| | |
|-----------------|-----------------------|
| Product name | Confidentiality level |
| B310s-518 | CONFIDENTIAL |
| Product version | Total 9 pages |
| V1.0 | |

B310s-518 Firmware Release Notes

V1.0

| | | | |
|-------------|----------------|------|----------|
| Prepared by | Guo xiaofei | Date | 2015-5-5 |
| Reviewed by | B310s-518 Team | Date | 2015-5-5 |
| Approved by | B310s-518 Team | Date | 2015-5-5 |



Huawei Technologies Co., Ltd.

All rights reserved

Revision Record

| Date | Revision version | FW-WebUI/HiLink Version | Change Description | Author |
|-------------|-------------------------|--------------------------------|-----------------------------|---------------|
| 2015-4-11 | 1.0 | FW 21.300.07.00.319 | The 1 th Version | Guo xiaofei |

Table of Contents

| | | |
|-----|--|---|
| 1 | Main Features | 4 |
| 2 | Hardware..... | 5 |
| 2.1 | Version Description | 5 |
| 2.2 | Hardware Specifications | 5 |
| 2.3 | Improvements in the Previous Version | 6 |
| 2.4 | Known Limitations and Issues | 7 |
| 3 | Firmware | 7 |
| 3.1 | Version Description | 7 |
| 3.2 | Firmware Specifications | 7 |
| 3.3 | Improvement in the Previous Version | 8 |
| 3.4 | Known Limitations and Issues | 9 |
| 4 | WebUI..... | 9 |
| 4.1 | Version Description | 9 |
| 4.2 | WebUI/HiLink Specifications | 9 |
| 4.3 | Improvement in the Previous Version | 9 |
| 4.4 | Known Limitations and Issues | 9 |
| 5 | Software Vulnerabilities Fixes | 9 |

B310s-518 Firmware Release Notes V1.0

| Abbreviations | description |
|---------------|-------------|
| | |
| | |

1 Main Features

The B310s-518 mainly supports the following features:

- LTE FDD (DL) data service of up to 150 Mbit/s
- LTE FDD (UL) data service of up to 50 Mbit/s
- LTE TDD (DL) data service of up to 112 Mbit/s
- LTE TDD (UL) data service of up to 10 Mbit/s
- DC-HSPA+ (DL) data service of up to 42 Mbit/s
- HSPA+ (DL) data service of up to 21.6 Mbit/s
- HSDPA (DL) data service of up to 14.4 Mbit/s
- HSUPA (UL) data service of up to 5.76 Mbit/s
- UMTS data service of up to 384 kbit/s
- EDGE data service of up to 236.8 kbit/s
- EDGE data service of download to 296 kbit/s
- GPRS data service of up to 85.6 kbit/s
- PS domain data service based on LTE/UMTS/GSM
- SMS based on CS/PS domain of GSM and UMTS, CS domain of LTE
- Wi-Fi
- Support for HUAWEI Mobile WiFi App
- Press and Play
- IPv6v4 /IPv4 dual stack
- Built-in DHCP Server, DNS RELAY and NAT
- Online software upgrade
- Traffic statistic
- LED indicators
- Built-in UMTS and WLAN high gain antenna LTE/GSM
- Windows XP SP3, Windows Vista SP1/SP2, Windows 7, Windows 8, Windows 8.1 (does not support Windows RT), MAC OS X 10.7, 10.8 and 10.9 with latest upgrades



2 Hardware

2.1 Version Description

Hardware Version: WL1B310FM (B310s-518)
 Platform & Chipset: Balong Hi6921 & AR 8035

2.2 Hardware Specifications

| Item | Specifications | |
|---------------------------|---|------------------------|
| Technical standard | WAN: LTE/ DC-HSPA+/HSPA+/HSPA/UMTS/EDGE/GPRS/GSM | |
| | WLAN: IEEE 802.11b/g/n | |
| Operating frequency | LTE: B1/B2/B4/B5/B7/B28 | |
| | HSPA+/HSPA/UMTS: B1/B2/B4/B5 | |
| | EDGE/GPRS/GSM: 1900/1800/900/850 MHz | |
| | WLAN: 2.4 GHz | |
| Internal memory | 512 MB Flash,256 MB Memory | |
| Maximum transmitter power | UMTS: 24 (+1/-3) dBm | |
| | WLAN | 802.11b: 20 (+/-3) dBm |
| | | 802.11g: 17 (+/-3) dBm |
| | | 802.11n: 17 (+/-3) dBm |
| Receiver sensitivity | UMTS: Confirm to 3GPP Requirements | |
| | WLAN 802.11b | -76 dBm@11 Mbit/s |
| | | -82 dBm@1 Mbit/s |
| | WLAN 802.11g: -65 dBm@54 Mbit/s | |
| | WLAN 802.11n: -64 dBm@65 Mbit/s | |
| WLAN speed | 802.11b: Up to 11 Mbit/s | |
| | 802.11g: Up to 54 Mbit/s | |
| | 802.11n: HT40 MCS15(300Mbit/s), | |
| | HT20 MCS15(144.4Mbit/s) | |
| Maximum power consumption | 12 W | |
| Power supply | AC: 100–240 V | |
| | DC: 12 V, 1 A | |
| External interfaces | WAN/LAN: 1 RJ45,GE | |
| | FXS:1 RJ11 | |
| | SIM card interface: standard 6-pin SIM card interface | |



| Item | Specifications | |
|------------------------|--|---|
| Indicators | Mode: | cyan: 4G mode blue: 3G mode yellow: 2G mode green: WAN mode Red: No SIM/USIM card is found, the PIN is not verified, or the SIM/USIM card is not working properly. Failed to connect to a mobile network |
| | Signal | One to three: Weak to Strong signal Off: out signal |
| | WPS/WIFI | White Blink: WPS open White Steady On: 2.4G WiFi is opened Off: 2.4G WiFi is closed |
| | LAN | On/Off |
| | Power | On/Off |
| Button | Power switch, Reset switch, WPS switch | |
| Antenna | <ul style="list-style-type: none"> • Built-in GSM/UMTS/LTE main diversity antenna • Built-in GSM/UMTS/LTE diversity antenna • Built-in WLAN antenna | |
| Dimensions (D x W x H) | 180 mm x126 mm x38mm | |
| Weight | about 226 g (Does not contain the power adapter) | |
| Temperature | Operating: 0°C to +40°C | |
| | Storage: -20°C to +70°C | |
| Humidity | 5% to 95% (non-condensing) | |

2.3 Improvements in the Previous Version

| Index | Case ID | Issue Description |
|-------|---------|-------------------|
| NA | | |



2.4 Known Limitations and Issues

| Index | Case ID | Issue Description |
|-------|---------|-------------------|
| NA | | |

3 Firmware

3.1 Version Description

| | |
|----------------------|-------------------------|
| Firmware Version: | 21.300.07.00.319 |
| Baseline information | BalongV700R110C30B300 |
| OS | VxWorks 6.8+linux 3.4.5 |

3.2 Firmware Specifications

| Item | Description |
|--------------------------|---|
| SMS | <ul style="list-style-type: none">• Writing/Sending/Receiving• Sending/Receiving extra-long messages• Storage: Up to 500 messages can be saved in the internal memory• New message prompt |
| Network connection setup | <ul style="list-style-type: none">• APN management: create, delete and edit.• Set up network connection |
| WLAN setup | <ul style="list-style-type: none">• SSID broadcasting and hiding• Open system and shared key authentication• ASCII and HEX keys• 64/128-bit WEP encryption• 256-bit WPA-PSK and WPA2-PSK encryption• AES encryption algorithm• TKIP and AES integrated encryption algorithm• Automatic adjustment of ratios• Display STA status• WLAN MAC filter |
| Firewall setup | <ul style="list-style-type: none">• Firewall Switch• LAN IP Filter• Virtual Server• DMZ Service |



| Item | Description |
|------------------------|---|
| NAT setup | <ul style="list-style-type: none"> • CONE NAT • Symmetric NAT • ALG • VPN passthrough |
| DHCP setup | <ul style="list-style-type: none"> • DHCP server enabling and disabling • Address pool of the DHCP server setup • DHCP lease time setup |
| IPv6v4/IPv4 dual stack | <p>DHCPv6/v4 server and client</p> <p>DNSv6/v4 server and client</p> <p>Display IPv6/v4 WAN address</p> |
| Other | <p>Network connection settings:</p> <ul style="list-style-type: none"> • Automatic network selection and registration • Manual network selection and registration |
| | <p>Network status display: signal, operator name, system mode, and so on.</p> |
| | <p>Selection of network connection types, for example:</p> <ul style="list-style-type: none"> • Support LTE networks ON/OFF |
| | <p>PIN management: activate/deactivate PIN, PIN lock, changing PIN, unblocking by using the PUK.</p> |
| System requirement | <ul style="list-style-type: none"> • Windows XP SP3, Windows Vista SP1/SP2, Windows 7, Windows 8 (does not support Windows RT) • Mac OS X 10.6, 10.7 and 10.8 with latest upgrades • Your computer's hardware system should meet or exceed the recommended system requirements for the installed version of OS |

3.3 Improvement in the Previous Version

| Index | Case ID | Issue Description |
|-------|---------|-------------------|
| | | |
| | | |
| | | |
| | | |



3.4 Known Limitations and Issues

| Index | Case ID | Issue Description |
|-------|---------|-------------------|
| | | |
| | | |
| | | |

4 WebUI

4.1 Version Description

WebUI Version: 17.100.09.00.03

4.2 WebUI/HiLink Specifications

| Item | Specifications |
|------|----------------|
| | |
| | |

4.3 Improvement in the Previous Version

| Index | Case ID | Issue Description |
|-------|---------|-------------------|
| | | |
| | | |

4.4 Known Limitations and Issues

| Index | Case ID | Issue Description |
|-------|---------|-------------------|
| | | |
| | | |

5 Software Vulnerabilities Fixes

| Software/Module name | Version | CVE ID | Vulnerability Description | Solution |
|----------------------|---------|--------|---------------------------|-------------|
| | | | | <i>None</i> |